

MODIFICATION AVAILABLE – PERFORMANCE ENHANCEMENT
CHARGEABLE TO CUSTOMER SERVICE / RELIABILITY
ENHANCEMENT CHARGEABLE TO CONTRACT IF THERE IS ONE.

6834B-07

S E R V I C E N O T E

Supersedes:
NONE

6834B Option J03 AC POWER SOURCE

Serial Numbers: 3601A00101/9999A99999 US09999999

The Control Board Assembly P/N 5064-0127 will NO longer be available as a replaceable part.

To Be Performed By: Agilent-Qualified Personnel or Customer

Parts Required:

P/N	Description	Qty.
0757-0405	162 Ohm Resistor	1
5063-3414 *	“NEW” Control assembly	1
5063-3415 *	“Restored” Control assembly	1

***Use either P/N 5063-3414 OR 5063-3415.**

Situation:

The tested assembly P/N 5064-0127 (MFPN 5001-727-1) is no longer available as a replaceable part.

ADMINISTRATIVE INFORMATION

SERVICE NOTE CLASSIFICATION:		
MODIFICATION AVAILABLE		
ACTION CATEGORY:	AGREEABLE TIME	<input type="checkbox"/> PERFORMANCE ENHANCEMENT <input type="checkbox"/> SERVICE / RELIABILITY ENHANCEMENT
LOCATION CATEGORY:	<input checked="" type="checkbox"/> CUSTOMER INSTALLABLE <input type="checkbox"/> ON-SITE <input checked="" type="checkbox"/> SERVICE CENTER	AVAILABLE UNTIL: OCT 2004
AUTHOR: cp PRODUCT LINE: PL33		
ADDITIONAL INFORMATION:		

© AGILENT TECHNOLOGIES, INC. 2003
PRINTED IN U.S.A.



May 22, 2003

Solution/Action:

The Control Board Agilent P/N 5064-0127, (MFPN 5001-727-1) will no longer be available as a replaceable part.

When there is a need for the Control Board P/N 5064-0127 the following action can be taken.

1. Modify the New "Standard" Control Board Assembly P/N 5063-3414 by changing (R59) FROM 14.7 Ohms P/N 0698-3428 TO 162 Ohms P/N 0757-0405. A label should be placed on the modified assembly with the part number 5064-0127. This part number will be used as an identifier.

2. Modify the "Restored" Control Board Assembly P/N 5063-3415 by changing (R59) FROM 14.7 Ohms P/N 0698-3428 TO 162 Ohms P/N 0757-0405. A label should be placed on the modified assembly with the part number 5064-0127. This part number will be used as an identifier.

3. Either assembly can be modified to become the P\N 5063-0127. It is recommended that the "Restored" Control Board Assembly P/N 5063-3415 be the first choice if modification is required.